

双级电动机直接型减速机的传动比和输入功率表

机号	B10	B20	B30	B31	B41	B42	B52	B53	B63	B74	B85	输出 转 速 r/min
	1512	1812	2212	2215	2715	2718	3318	3322	3922	4527	5533	
	X32	X42	X52	X53	X63	X64	X84	X85	X95	X106	X118	
输入转速 r/min	1500											
扭 矩 N·m 输入功率kw 传动比	250	500	980	1176	2156	2700	4500	4508	7680	11000	18000	
121 (11×11)	0.55	0.75	1.1	2.2	2.2	4	5.5	7.5	7.5			12.3
187 (17×11)	0.37	0.55	0.75	1.5	1.5	3	4	5.5	7.5	11	15	8.0
289 (17×17)	0.25	0.55	0.75	1.1	1.5	2.2	3	4	5.5	11	15	5.2
391 (23×17)	—	0.37	0.55	0.75	1.1	1.5	2.2	3	5.5	7.5	11	3.8
473 (43×11)	—	0.37	0.55	0.75	1.1	1.5	1.5	2.2	4	5.5	7.5	3.2
493 (29×17)	—	0.37	0.55	0.75	1.1	1.1	1.5	2.2	4	5.5	7.5	3.0
595 (35×17)	—	0.25	0.37	0.55	0.75	1.1	1.1	2.2	3	4	7.5	2.5
731 (43×17)	—	—	0.37	0.55	0.75	0.75	1.1	1.5	3	3	5.5	2.0
841 (29×29)	—	—	0.37	0.37	0.55	0.75	0.75	1.5	2.2	2.2	5.5	1.8
1003 (59×17)	—	—	0.37	0.37	0.55	0.75	0.75	1.1	1.5	2.2	4	1.5
1225 (35×35)	—	—	—	0.37	0.55	0.55	0.75	1.1	1.5	2.2	3	1.2
1479 (87×17)		—	—	—	0.55	0.55	0.55	—	1.1	—	2.2	1.0
1505 (43×35)		—	—	—	—	—	—	—	—	—	—	1.0
1849 (43×43)		—	—	—	—	—	—	—	—	—	—	0.8
2065 (59×35)		—	—	—	—	—	—	—	—	—	—	0.7
2537 (59×43)		—	—	—	—	—	—	—	—	—	—	0.6
3481 (59×59)		—	—	—	—	—	—	—	—	—	—	0.4
4189 (71×59)		—	—	—	—	—	—	—	—	—	—	0.3
5133 (87×59)		—	—	—	—	—	—	—	—	—	—	0.3
7569 (87×87)						—	—	—	—	—	—	0.2
备 注	在严格限制许用扭矩下，在“—”处的输入功率采用表中该机号下的最小额定输入功率。根据需要，还可满足顾客表中没有列出的其他传动比。											